

# **User Guide**

#### Introduction

The carbon dioxide sensor is an industrial-grade sensor with high integration. The data is sent from the internal chip of the sensor to the computer through the modbus-RS485 interface, and multiple sensors can be connected to the bus network to realize real-time monitoring of multiple field environments. It has super stability and anti-interference ability, strong product protection performance and first grade lightning protection, which can be used in agricultural industry and other occasions.



#### **Use Case Scenarios**

It is widely used in agricultural greenhouses, intelligent buildings, workshops, warehouses, pharmacies, libraries, museums, laboratories, offices, ventilation ducts and other places where carbon dioxide concentration needs to be monitored.

#### **Features**

- High precision, wide range, good consistency.
- Standard audio interface design, easy to plug.
- Super stability and anti-interference.
- The product has strong protective performance and first grade lightning protection.

### **Specification**

Specifications Specification Specificat								
Model	UB-CO <sub>2</sub> -P1	UB-CO <sub>2</sub> -P2	UB-CO <sub>2</sub> -P3					
Measuring Range	CO <sub>2</sub> : 400 ~ 10000ppm (Max: 0 ~ 40000ppm) Temperature: -40 ~ 70°C Humidity: 0 ~ 100%RH	CO <sub>2</sub> : 400 ~ 2000ppm (Max: 0 ~ 40000ppm)  Temperature: -10 ~ 60°C  Humidity: 0 ~ 100%RH	CO <sub>2</sub> : 400 ~ 2500ppm (Max: 400 ~ 10000ppm)					
Measuring Accuracy	CO <sub>2</sub> : ±(30ppm + 3%) (@400 ~ 10000ppm) Temperature: ±(0.4°C + 1%) (@0 ~ 50°C) Humidity: ±3%RH (@25°C, 0 ~ 100%RH)	CO <sub>2</sub> : ±(50ppm + 5%) (@400 ~ 2000ppm) Temperature: ±0.8°C (@15 ~ 35°C), ±1.5°C (@-10 ~ 60°C) Humidity: ±6%RH (@15 ~ 35°C, 20 ~ 65%RH), ±9%RH (@-10 ~ 60°C, 0 ~ 100%RH)	CO <sub>2</sub> : ±(40ppm + 3%) (@400 ~ 2500ppm)					
Power Supply	DC 5 / 12V	DC 5 / 12V	DC 5 / 12V					
Max Current	267mA (@5V), 86mA (@12V)	260mA (@5V), 125mA (@12V)	498mA (@5V), 194mA (@12V)					
Connector	Audio							
Dimensions	110 * 85 * 44mm							
Cable Length	3m							
Communication Protocol	RS485 Modbus RTU Protocol							
RS485 Address	0x61							
Baud Rate	1200 bit/s, 2400 bit/s, 4800 bit/s, 9600 bit/s, 19200 bit/s (default)							

# **Wiring Instruction**



### **Communication Protocols**

### 1. Communication Basic Parameters

Communication Basic Parameter					
Coding System	8-bit binary				
Data Bit	8 bits				
Parity Checking Bit	none				
Stop Bit	1 bit				
Error Checking	CRC Check				
Baud Rate	1200 bit/s, 2400 bit/s, 4800 bit/s, 9600 bit/s, 19200 bit/s (default)				

### 2. Data Frame Format

The Modbus-RTU communication protocol is used in the following format:

- Initial structure ≥ 4 bytes in time.
- Address code: 1 byte, default 0x61.
- Function code: 1 byte, support function code 0x03 (read only) and 0x06 (read / write).
- Data area: N bytes, 16-bit data, high byte comes first.
- Error check: 16-bit CRC code.
- End structure ≥ 4 bytes of time.

Request											
Slave Addres	S	Function (	Code Register Address		No. of Registe	ers	CRC LSB		CRC MSB		
1 byte		1 byte	e 2 bytes		bytes	2 bytes		1 byte		1 byte	
Response											
Slave Address	Fur	nction Code	No. of	Bytes	Content 1	Content 1		***	Conte	nt n	CRC
1 byte		1 byte	1 byte		2 bytes	2 bytes		2 byt		es	2 bytes

# 3. Register Address

Register Address						
Address	Content	Register Length	Function Code	Description of Definitions		
0x0028	CO <sub>2</sub>	2	03	IEEE 754 floating point		
0x0032	Temperature	2	03	IEEE 754 floating point		
0x0036	Humidity	2	03	IEEE 754 floating point		
0x0064	Address	1	03/06	1 ~ 255 (UB-CO <sub>2</sub> -P1 unsupported)		
0x0065	Baud Rate	1	03/06	5:4800, 6:9600, 7:14400,		
			03/06	8:19200, 9:38400, 10:115200		